

# DC WallBox

## Replace 3G module

Jan. 8, 2020

DS12\_v2.0





# Tool Preparation



**Screwdriver**



**Diagonal Pliers**



**Needle nose**




# Relevance part number

Title	Part number	Remark
Communication BD (Huawei 609)	3798100045-S	For US/EU model, already EOL
Communication BD (Huawei 709)	5505605078	For US/EU model, start using since 2018.09
Communication BD (Ublox)	3798100046-S	For JP model


# Remove side cover

Remove filter cover with T20 torx driver

- Release the two screws on top.
- Release the two screws on bottom and pull out the latch.
- Open and remove the filter cover.





Remove protection cover






# Step 1. Remove Micro-USB cable




## Step 2. Pull out 3G module

1. Pull blue latch
2. Pull out 3G module a little bit



## Step 3. Cut off the cable tie








## Step 4. Pull out the antenna cable

Pull out the antenna cable so that the 3G module can be pulled out more and disassembly antenna cable from 3G module easily.









## Step 5. Disassembly antenna cable

Disassembly antenna cable from 3G module by needle nose or hand.




or






## Step 6. Disassembly power cable

Disassembly the power cable of 3G module, and then 3G module can be pulled out completely.





## Step 8. Install 3G module



Recommend to tighten  
the antenna cable



# Smarter. Greener. Together.

To learn more about Delta, please visit [www.deltaww.com](http://www.deltaww.com).

