





DELTA ELECTRONICS, INC.



DeltaSolar Application

Operation Manual for Android system

www.deltaww.com

5.1.2. Inverter FW Update

[Inverter FW Update - connection of DC1]

LOCAL SETTING -> Maintenance -> Inverter Firmware Update

GET CURRENT FIRMWARE VERSIONS

service for the FW type.

Select the method to get Internet ability.

Downloading...

46

Click "OK".

Updating...

Success.

Inverter FW Update
GET CURRENT FIRMWARE VERSIONS
Firmware Type :
Firmware Version : 02.01
Download Status : Finished
UPDATE SINGLE INVERTER
SAME MODEL UPDATE
Update Status
Success

[Inverter FW Update - connection of inverter]

LOCAL SETTING -> Maintenance -> Firmware Update

Enter Firmware update page. to Internet. Firmware Update Inverter Model: Inverter Model: Firmware Type: Click on 'OK'. The APP will automatically direct you to the page for Router connection. OK Status:

Click "Inverter Model".

date				
A DELTA				

Select the Inverter model for FW update.

Click "OK" the app will ask user connect

Select the method to get Internet ability.

Select FW type, please confirm with local service for the FW type.

H2.5~H5A Flex
H3A_222
H5A_222
H4J-22
H5.5J22
H6J_24
H6J
H5E_220

Click "Load Hex File".

After download complete, click "Scan inverter".

Select the Inverter serial number for FW update.

Serial Number	dBm	Status		
Delta-05Q18500961W0	-33			
Delta-09Y19800016W0	-40			
Ca-09Y19700007W0	-53			
Delta-PVT206006800H	-70			
Update Inverter				
Firmware Version :				
02.	07			
Information:				
Product ID : 52000200				

Click "Update Inverter".

← Firmware Update	← Firmware Update	Scan inverter If your device is not on the list. Please click on scan and move closer to your device.
Serial Number dBm Status Delta-05Q18500961W0 -33 Delta-09Y19800016W0 -40 Checking connection of inverter Delta-09Y19700007W0 -53 Delta-PVT206006800H -70	Serial Number dBm Status Delta-05Q18500961W0 -33 -33 Delta-09Y19800016W0 -40 Upgrading Delta-09Y19700007W0 -53 -53 Delta-PVT206006800H -70 -70	Serial Number dBm Status Delta-05Q18500961W0 -33 Delta-09Y19800016W0 -40 Success Delta-09Y19700007W0 -53 Delta-PVT206006800H -70
ر	Transmission: 8% 136	Update inverter
Firmware Version :	Firmware Version :	Firmware Version :
02.07 Information: Product ID : 52000200 Processor : 0 Start address : 08020000 Stop address : 080FFFFF CheckSum : 0x064F OK	02.07 Information: TCPGetPIDCmd done ReqBoot1Tcp done ReqBoot2Tcp done ProcessorSelectTCP done BankSelectTCP done InternalProcTCP done	02.07 Information: BurnProcessTCP done BankCloseProcTCP done BurnDoneProcTCP done InternalProcTCP_final done Total Tx Len :227968

Click "OK".

Upgrading...